



Avaya J-Series Telephone Instructions

Function	Steps	Function	Steps
To Answer a Call	<ul style="list-style-type: none"> • Pick up the Handset – or – Press [SPEAKER] 	To Transfer a Call To Another Extension	<p><u>DO NOT PRESS HOLD</u></p> <ul style="list-style-type: none"> • Press [TRANSFER] • Enter the “Transfer to:” extension • Press [TRANSFER] or Complete immediately. <p>You can also wait for the called party to answer and announce the call before pressing [TRANSFER] or Complete</p> <p>Return the caller to you</p> <ul style="list-style-type: none"> • If the called party does not answer or does not want the transfer, press [DROP]. To return to the held call, press the call appearance key where the call is blinking.
To Make a Call Outside the Office	<ul style="list-style-type: none"> • Pick up the Handset – or – Press [SPEAKER] • Dial the access code “9” • Dial the telephone number 		
To Call a Telephone Extension In the Office	<ul style="list-style-type: none"> • Pick up the Handset – or – Press [SPEAKER] • Dial the extension number 		
Muting a Call	<ul style="list-style-type: none"> • Press [Mute] during a call so that the other person on call cannot hear you. • Press [Mute] again to unmute the call. <p><i>Note: When you mute the call, the Mute button light is on and the top line displays the Mute icon</i></p>	To Make a 3-Way Conference Call	<ul style="list-style-type: none"> • Make or answer the first call • Press [CONFERENCE] <p><i>This will place the first call on hold automatically</i></p> <ul style="list-style-type: none"> • Make the second call • Press [CONFERENCE] <u>again</u> to begin the conference <p>If the called party does not answer or does not want to join the conference, press [DROP]. To return to the held call, press the call appearance key where the first call is blinking.</p> <p>Viewing the details for a conference:</p> <ul style="list-style-type: none"> • Press Details button to access the details on the participant
To Place a Call on Hold To Return to the Caller	<ul style="list-style-type: none"> • Press the [HOLD] soft key • Press Resume, OK button, or Extension or Line key with the flashing indicator <p><i>Note: The line flashing very quickly or without a _ under the handset is YOUR held call. If the light(s) blink slowly or if there is a _ under the handset, it was placed on hold by someone else.</i></p>		
To Hang-up	<ul style="list-style-type: none"> • Press [DROP] • OR Press [SPEAKER] if the call is “handsfree” • OR Return the handset to the cradle 		
DND (<i>Do Not Disturb</i>)	<ul style="list-style-type: none"> • Press [DND] to temporarily disable ringing and forward all calls directly to voicemail • Press [DND] again to cancel <p>No Button Programmed:</p> <p>To activate:</p> <ul style="list-style-type: none"> • Press Main Menu  • Select Features • Use the Down Arrow key to go to the Do not disturb screen • Select Do not disturb <p>To Deactivate:</p> <ul style="list-style-type: none"> • Press Main Menu  • Select Features • Use the Down Arrow key to go to the Do not disturb screen • Select Do not disturb 	Transfer to Voicemail	<ul style="list-style-type: none"> • Press [MESSAGE] Envelope Button (Do not place caller on hold) • Enter the extension number • Press the Select soft key to transfer the call • To exit the Transfer Menu on Display, Press Cancel <p>OR</p> <ul style="list-style-type: none"> • Press Transfer then dial # plus the Mailbox number
Redial – Last Number	<ul style="list-style-type: none"> • To have the phone dial the last number you dialed press Redial then Call 		
Redial – Search	<ul style="list-style-type: none"> • To scroll through a list of recently dialed numbers press Redial, then scroll through the redial list • Highlight your selection then press Call 	Transfer a Caller to a Mailbox	

Avaya J-Series Telephone Instructions

Function	Steps	Function	Steps
Page (if applicable)	Press the [Page] key to make an Announcement through phone speakers or dial the [Page] access code	Leave Message For <u>Internal</u> Callers Leave a message without Ringing an Extension	<ul style="list-style-type: none"> • Pick up Handset • Enter # plus the mailbox number, (Ex: #2221) • At the tone, leave a message

Parking a call is similar to holding a call. However, parked calls can be unparked by other users on the phone system. (Park codes 500-509)

To Park Call:

Press **Park** key

A park code will be displayed in the screen (Ex:500)

Hang up the phone

-----OR-----

Press Transfer

Dial *37*ext number # (individual's extension you want to park the call to)

To Unpark Call: (Retrieve the Call)

Pick up the handset or press speaker button

Dial the park access code (Ex:500)

To Unpark Call: (Retrieve the Call)

Pick up the handset or press speaker button

Dial the park access code (Ex:500)










Call is connected








-----OR-----

If call is parked via the extension number

Pick up the handset or press speaker button
















Dial the short code: *38* ext number#

Function	Steps	Function	Steps
	<p>To Dial from Contacts</p> <p>1. Press  Contacts key. (Contact menu is displayed) </p> <p>directory entries you want displayed: ALL (System Directory, Personal & External) PERSONAL (Individual Speed Dial) EXTERNAL (Shared Speed Dial) </p> <p>list or start dialing the name to find matching entries</p> <p>4. Press Call when your selected contact is highlighted</p>		<p>To View the Call History</p> <p>1. Press the  RECENTS button. The display will change to show your call log records. The caller's name is shown if known, otherwise the number. </p> <p>records you want to view. (<i>All, Missed, Incoming & Outgoing</i>)</p> <p>If you have any new missed call records, the  Recent button lamp is illuminated. </p> <p>records.</p> <p>4. Press Details to view additional information</p> <p>5. To call external number: Lift handset, dial 9, then press Call</p>





<p>(Personal Speed Dial) Up to 250 Entries</p>	<p align="center"><u>To Add an Entry – Personal</u></p> <ol style="list-style-type: none"> 1. Press  Contact key. (<i>Contact menu is displayed</i>) 2. Press the New soft key. 3. Enter Name <i>Example: To spell the name “Don” on your Dial Pad: Press 3 once, for the Letter D. Press 6 three times, for the Letter O Press 6 twice, for the Letter N</i> 4. Enter Number 5. Press the Save soft key. (Your new Entry is now saved) The new entry will show in ALL or PERSONAL display <p align="center"><u>To Delete an Entry</u></p> <ol style="list-style-type: none"> 1. Press  Contacts key 2. Find and highlight your entry to be deleted 3. Press the More soft key 3. Press the Delete 4. Press the Delete soft key again to confirm the action. <p>Press the Cancel soft key to exit without making changes *Note: You can only delete/modify your Personal entries</p>	<p>Change Ringer</p>	<ol style="list-style-type: none"> 1. Press the  Main Menu button 2. Scroll to Settings, and press Select. 3. Scroll to Audio, and press Select. 4. Scroll to Personalize ringing, and press Select. 5. Scroll to one of the following options: <ul style="list-style-type: none"> • Primary • Team Key • Bridged CA • Call Pickup 6. Press one of the following: <ul style="list-style-type: none"> • Select • OK 7. Scroll to the ringtone, and press Select. 8. (Optional) To play the ringtone, press Play. 9. Press Save. <p>Press Cancel soft key if you wish to make no changes</p>
<p>(Shared Speed Dial) **Programmed by System Administrator</p>	<p align="center"><u>To Dial from Shared External Directory</u></p> <ol style="list-style-type: none"> 1. Press  Directory key (arrow right to External Display) 3. Use the  up and down  arrow keys to scroll through the list or start dialing the name to find matching entries 4. Press Call when your selected contact is highlighted 	<p>Change Background</p>	<ol style="list-style-type: none"> 1. Press the  Main Menu button. 2. Scroll to Settings, and press Select. 3. Scroll to Display, and press Select. 4. Scroll to Background, and press Select. 5. Scroll down to the new image. 6. (Optional) To preview the image, press Preview and then press Dismiss. 7. Press one of the following: <ul style="list-style-type: none"> • Select • OK 8. Press one of the following: <ul style="list-style-type: none"> • Save • OK



Avaya J-Series Telephone Instructions

General Icons:

Icon	Description	Icon	Description
	Microphone is muted.		Call is active.
	Missed call on your phone.		Call is on hold.
	Incoming call; indicates you have answered this call.		Call redirection
	Outgoing call; indicates you have made this call.		Conference is active.
	Bridged call; indicates you are on a bridged call.		Conference is on hold.
	Call is active on a bridged line.		Use the Right or Left navigation arrow to see more pages/screens/options.
	Incoming call is alerting.		Scroll left for other options.
			Scroll right for other options.

Main Menu Icons:

Icons	Name	Description
	Features	To access administrator activated features.
	Applications	<ul style="list-style-type: none"> To access phone applications such as Contacts, Recents, and activate screen saver. To sign off the phone, to protect your settings, or to let another user to log in.
	Settings	To change your phone settings, customize button labels, adjust brightness, audio settings, assign speed dial entries, and more.
	Network Information	To check phone settings or network settings.

Icons	Name	Description
	Administration	To access administration settings.
	About	To display the phone software version.

Avaya J-Series Telephone Instructions

1. Beacon LED – Displays a red light for visual alerts such as incoming call and voicemail message
2. Phone display – Displays 2 areas. Top Bar – Communication status, time & date, and device status. Application area – Application header, application content and softkey labels
3. Line Keys – Used to select the corresponding row. Each line key has an LED that displays visual features such as, Red light-disabled features, Green light-incoming call and enabled features or Red and Green light-off hook status of the phone
4. Soft Keys – Select the corresponding label of context-specific action
5. Navigation Key – Navigate the phone screen. Up and Down arrow keys, to scroll up and down. Right and left arrow keys, to move the cursor in the text input field and to toggle values.
6. Phone Key – Displays the phone screen
7. Navigation Key – OK button to select the action assigned the first soft key
8. Main Menu – Displays a list of options: Options & Settings, network information, VPN settings, browser, log out, and about the phone
9. Contacts – Displays the entries in your contact list
10. Recents – Displays the list of calls in Call history
11. Voicemail – Used to access voicemail
12. Headset – Used if there is a headset connected to the phone
13. Speaker – Used to access speaker for handsfree capability
14. Volume – Used to adjust the volume for the ringtone when handset is in the cradle. Adjust the volume of the caller when a call is connected. The (+) plus key increased the volume, the (-) minus key decreases the volume
15. Mute Button – Used to mute and unmute the outgoing audio. This can be used with speaker or handset

J139



J179



J159 Telephones



1. Beacon LED – Displays a red light for visual alerts such as incoming call and voicemail message
2. Phone display – Displays 2 areas. Top Bar – Communication status, time & date, and device status. Application area – Application header, application content and softkey labels
3. Line Keys – Used to select the corresponding row. Each line key has an LED that displays visual features such as, Red light-disabled features, Green light-incoming call and enabled features or Red and Green light-off hook status of the phone
4. Soft Keys – Select the corresponding label of context-specific action
5. Phone Key – Displays the phone screen
6. Voicemail – used to access voicemail
7. Redial – used to redial the most recently dialed number from any screen on the phone
8. Speaker - Used to access speaker for handsfree capability
9. Hold – used to place and active call on hold and resume a held call
10. Line Keys – use to select the corresponding line or feature.
11. Secondary Display – Provided quick access to lines appearances, features and phone menus
12. Left/Right keys – used to navigate the Secondary Display Screen
13. Mute – Used to mute and unmute the outgoing audio
14. Navigation Key – Navigate the phone screen. Up and Down arrow keys, to scroll up and down. Right and left arrow keys, to move the cursor in the text input field and to toggle values.
15. Main menu – Displays the list of options, such as Features, applications, Setting and Network information
16. Contacts – Displays the entries in you contact list
17. Recents – Displays the list of all calls
18. Transfer – Used to transfer a call
19. Headset – used to turn on headset and toggle your call from the speaker to headset
20. Conference – Used to initiate a conference call and also to add a participant to a conference call
21. Dial Pad keys – Used to dial the phone extensions or enter alphanumeric characters and symbols
22. Handset – Used to receive and make calls
23. Volume – Used to adjust volume of a handset, speaker or ringtone. (+) to increase, (-) to decrease
24. Mic – The MIC of the phone